EITEL-McCULLOUGH, INC. SAN BRUNO, CALIFORNIA

LOW-MU TRIODE MODULATOR **OSCILLATOR** AMPLIFIER

The Eimac 75TL is a low-mu power triode intended for use as an amplifier, oscillator, or modulator. It has a maximum plate dissipation rating of 75 watts and a maximum plate voltage rating of 3000 volts at frequencies up to 40 Mc. Forced-air cooling is not required in properly designed equipment operating at frequencies below 40 Mc.

The 75TL in Class-C R-F service will deliver up to 225 watts plate power output with 8 watts driving power. Two 75TL's in Class-B modulator service will deliver up to 350 watts maximum-signal plate power output with 5 watts driving power.

plate power	output wit	h 5 w	ratts o	drivin	g po	wer.														1	- 8	
			G	ENE	RAI	L C	HAR	ACT	ERIS	STIC	:s							12			8	
ELECTRIC	AL																			1	. 8	1
Filament:	Thoriated	tun	gsten																		· you	
	Voltage		-		-	-	-	-		-		-			5.0		olts			,	. 1	,
	Current					23	2	2	12		-		40		6.25	amp	eres				1	
Amplifica	tion Facto	or (/	Avera	ge)	•	-	٠.	2	-	-		-	-			2001013.EU	12		100	-6		19
Direct Int	terelectrod	le Ca	pacit	ance	s (Av	erag	e)													6	1	- 1
	Grid-Plate	е	-	-		-	43	-	-	-	-	-	-	-		2.4	uuf	- 1			1	
	Grid-Filar	ment			-	28	23	-	_		-	-	2			2.6					1	
	Plate-Filar	ment	il Int a e	-		-		-	-	-	:	-	-	-		0.4					-	
Transcond	ductance	(10=	225	ma.,	E.=	2500	v.)	*	-	-	-		97	15		μm						1.2
Highest	Frequency	for	Max	imum	Rat	ings		-	4	•	-	-	-	-		40	Mc.					-
MECHAN	ICAL																					-12
Base													Mad		4-pin	L		- 1			1	1
Basing	550 950 920 920		0.70	050	20	-	- 5	- 5			-				utline	1000		- 1			2	0
Socket			lohn	-	vne h	ا ما	22-22	4, Natio	onal	tuna	No.	YC.4					1000	ı	_	_		
Mounting	Position		-	2011 1	be i				- III	.700	140.		JI 01		or ec	uiva	ent		Ve	rtical, ba	se do	wn or I
Cooling	·	530		959	9356	1070	55	0	0	0		- 0x			100	•				nvection		
- 10 50 million - 1	Temperat	ture (of Pla	te ar	d G	id S	nals	- 2	0	0	12	10	- 12	200	100				* 1858 **			225°
	nded Hea																					
	Plate		-		-	-							2								Eim	ac HR
	Grid	•		0.00	10.00		-	-	-	-	-	-							•	•		ac HR
Maximum	Overall D	Dimer	nsions	:																		
	Length				-		40	20	2	-	<u>_</u>	12	12		84	-					7.25	inches
	Diameter		4		_	-	-	-	_	-	-	-	-			-					2.81	inches
Net Wei	ght -		-	7.5	70	-	-	-	-	-		- 7									3	ounces
Shipping	Weight (Avera	age)	(*)	-	70		-	100	=	-	-	18		-		18				1.5	pound
RADIO FR AND OSC Class-C Telegr MAXIMUM RA	ILLATO aphy (Key-c	R	condit	tions,	l tube	e)					O-C Pla O-C Pla O-C Gr	ate Vol rid Vol ate Cu rid Cu I-F Gri	tage rrent rrent id Inpi	ut Vo	oltage	:		to 40	1000 -150 215 28 320	1500 —250 167 22 355	—3 I	50 ma. 21 ma. 25 volt
O-C PLATE VO	JRRENT	:	: :		•	3000	MAX	VOLTS		P	riving	Power	er (ap	prox	.)	:	: :		215	250		8 wat
LATE DISSIPA	ATION	200		11		75	MAX	WATTS		P	late I	Dissipa	Outpu			17		9	75 140	75 175		75 wat
					•	13	MAA	WAIIS					-							1/5		25 wat
LATE MO				10								AL OP ate Vo	ERATIO	ON.	(Frequ	encie:	s up i	0 40	Mc.)	1500	20	00 volt
REQUEN										T	otal E	Bias Vo	oltage		•				-250 -130	-370 -260	- <u>5</u>	00 volt
lass-C Teleph				modures o	10000					6	erid F	Resisto	r -	:	•				7500	6000	-60	00 ohm
AXIMUM RA		quenc	ies up	to 40	Mc.)						C Gr	ate Cu	rrent (a	ppr	ox.)	:	: :		135	130		30 ma. 20 ma.
-C PLATE VO		3 4 5		1121	20			VOLTS		P	eak R	-F Gri	d Inpu	it Vo	ltage	(app	ox.) -		410	545	6	95 volt 14 wat
-C PLATE CU		•	•	•	•	3 5 5	MAX.			Ġ	rid I	Dissipa	er (ap				. :		2	3		4 wat
LATE DISSIP		5			•			WATTS		P	late	Dissipa	ation	:		:	: :		135	195 50		60 watt
RID DISSIPA	33.003.00)* E	• •					WATTS		P	late f	ower	Outpu	t -	•	•			85	145	2	10 wat
AUDIO FR AND MOI Hass—AB,	DULATO	R		VER	AM	IPLI	FIER				-C Pla	rid Vo			: :	:		:	ubes i	1500 —130 130 67	2000 —190 190 50	
AXIMUM RA		r tub	0)								dax-216	gnai L	O-C PI	ate !	Curren	i :				143	130	ma.
-C PLATE VO					*	3000	MAX	VOLTS		E	ffectiv	Power Loa	d. Pla	te-te	o-Plate		:			10,200	21,200	watt
MAX-SIGNAL		CUI	RRENT		+1	225	MAX	MA.		h	Aax-Si	anal P	late Po	ower	Outp	ut .	ube)	•	•	64 75	110 75	watts
LATE DISSIPA								WATTS		Ť												

IF IT IS DESIRED TO OPERATE THIS TUBE UNDER CONDITIONS WIDELY DIFFERENT FROM THOSE GIVEN UNDER "TYPICAL OPERATION", POSSIBLY EXCEEDING MAXIMUM RATINGS, WRITE EITEL-McCULLOUGH, INC., FOR INFORMATION AND RECOMMENDATIONS.



AUDIO FREQUENCY POWER AMPLIFIER AND MODULATOR

Class-AB,

MAYIMIN DATINGS (Per tube)

MAXIMUM KATINGS (FEF IL	Del						
D-C PLATE VOLTAGE -	3	-			3000	MAX.	VOLTS
MAX-SIGNAL D-C PLATE C	URRE	NT	:	1	225	MAX.	MA.
PLATE DISSIPATION -					75	MAX.	WATTS
GRID DISSIPATION					13	MAX.	WATTS

D-C Plate Voltage		-	-			1000	1500	2000	volts
D-C Grid Volta	ge1 -	(C) (S	7.	*0	-	-70	-130	-190	volts
Peak A-F Grid	Input V	oltage	(per	tube)	215	250	300	volts
Zero-Signal D-C	Plate	Curre	ent		-	100	67	50	ma.
Max-Signal D-C					-	350	285	250	ma.
Max-Signal Avg	. Drivin	g Powe	r (ap	ргох	.)	7	6	5	watts
Max-Signal Pea				-	-	26	23	19	watts
Effective Load				-	-	5300	11,000	18,000	
Max-Signal Plat				+	-	200	280	350	
Max-Signal Plat	e Dissi	pation	(per	tube	•)	75	75	75	watts
Total Harmonic	Disto	rtion			-	2.0	4.5	6.0	per cent
1Adjust to giv	e state	d zero	-sign	al p	late	current	The	effective	arid.
circuit resistance	a for	aach to	ha r	nurt.	not	ovened	250 000	ohme in	class.

APPLICATION

MECHANICAL

Mounting—The 75TL must be mounted vertically, base down or up. The plate and grid leads should be flexible. The tube must be protected from vibration and shock. Cooling—Heat Dissipating Connectors (Eimac HR-3 and HR-2) should be used at the plate and grid terminals of the 75TL. If the free circulation of air around the tube is restricted, a small fan or centrifugal blower should be used to provide additional cooling for the plate and grid seals.

Cooling requirements will be met if the temperature of the plate and grid seals is not allowed to exceed 225°C. One method of measuring these temperatures is provided by the use of "Tempilaq", a temperature-sensitive lacquer available from the Tempil Corporation, New York 11, N.Y.

ELECTRICAL

Filament Voltage—For maximum tube life the filament voltage, as measured directly at the base pins, should be the rated value of 5.0 volts. Variations must be kept within the range of 4.75 to 5.25 volts.

Bias Voltage—Although there is no maximum limit on the bias voltage which may be used on the 75TL, there is little advantage in using bias voltages in excess of those given under "Typical Operation," except in certain very specialized applications. Where bias is obtained by a grid leak, suitable protective means must be provided to prevent excessive plate dissipation in the event of loss of excitation.

Plate Voltage—The plate-supply voltage for the 75TL should not exceed 3000 volts. In most cases there is little advantage in using plate-supply voltages higher than those given under "Typical Operation" for the power output desired.


Grid Dissipation—The power dissipated by the grid of the 75TL must not exceed 13 watts. Grid dissipation may be calculated from the following expression:

 $P_{g} = e_{cmp}I_{c}$ where $P_{g} = Grid$ dissipation, $e_{cmp} = Peak$ positive grid voltage, and $I_{c} = D$ -c grid current.

e_{cmp} may be measured by means of a suitable peak voltmeter connected between filament and grid.² In equipment in which the plate loading varies widely, such as oscillators used for radio-frequency heating, care should be taken to make certain that the grid dissipation does not exceed the maximum rating under any condition of loading.

Plate Dissipation—The plate of the 75TL operates at a visibly red temperature at its maximum rated dissipation of 75 watts. Plate dissipation in excess of the maximum rating is permissible only for short periods of time, such as during tuning procedures.

²For suitable peak v.t.v.m. circuits see, for instance, "Vacuum Tube Ratings", Eimac News, January, 1945. This article is available in reprint form on request.





DRIVING POWER vs. POWER OUTPUT

The three charts on this page show the relationship of plate efficiency, power output and grid driving power at plate voltages of 1000, 1500 and 2000 volts. These charts show combined grid and bias losses only. The driving power and power output figures do not include circuit losses. The plate dissipation in watts is indicated by $P_{\rm p}$.

Points A, B, and C are identical to the typical Class C operating conditions shown on the first page under 1000, 1500, and 2000 volts respectively.

